
Appendix H

Typical EMF Levels for Power Transmission Lines

Ту	pica	EMF Levels	for Pov	ver Transmission Lines*	
115 kV	ŤŤ	Approx. Edge of Right-of-Way 15 m (50 ft)	30 m (100 ft)	61 m (200 ft)	91 m (300 ft)
Electric Field (kV/m)	1.0	0.5	0.07	0.01	0.003
Mean Magnetic Field (mG)	29.7	6.5	1.7	0.4	0.2
230 kV		Approx. Edge of Right-of-Way 15 m (50 ft)	30 m (100 ft)	61 m (200 ft)	91 m (300 ft)
Electric Electric (IA (IA)		I		I	
Electric Field (kV/m)	2.0 57.5	1.5 19.5	0.3 7.1	0.05 1.8	0.01 0.8
Mean Magnetic Field (mG)	57.5	19.5	7.1	1.8	0.8
500 kV	P	Approx. Edg of Right-of-W 20 m (65 ft)	ay 30 m (100 ft)	61 m (200 ft)	91 m (300 ft)
iviean iviagnetic Field (mG)	80.7	29.4	12.6	3.2	1.4
Electric Field (kV/m) Mean Magnetic Field (mG)	7.0	20 m	30 m		

Magnetic Field from a 500-kV Transmission Line Measured on the Right-of-Way



Electric fields from power lines are relatively stable because line voltage doesn't change very much. Magnetic fields on most lines fluctuate greatly as current changes in response to changing loads. Magnetic fields must be described statistically in terms of averages, maximums, etc. The magnetic fields above are means calculated for 321 power lines for 1990 annual mean loads. During peak loads (about 1% of the time), magnetic fields are about twice as strong as the mean levels above. The graph on the left is an example of how the magnetic field varied during one week for one 500-kV transmission line.

*These are typical EMFs at 1 m (3.3 ft) above ground for various distances from power lines in the Pacific Northwest. They are for general information. For information about a specific line, contact the utility that operates the line.

Source: Bonneville Power Administration, 1994.